



## Product Data Sheet

Lineární zářivka T5 (maso)

## LT 21W T5/079 Food light NBB



Order number

**106012000**

Unit EAN13 code

**8595209922106**

### General information

Model/Description	<b>Zářivková trubice</b>
Finish	<b>Lineární</b>
Brand/Manufacturer	<b>NBB</b>
Lamp type	<b>T5</b>
Nominal service life (h)	<b>20000 h</b>
Colour	<b>Ostatní</b>
Socket	<b>G5</b>
Dimmable	<b>Ano</b>
Energy efficiency class (canceled regulation!)	<b>A</b>
Ignition strip	<b>Ne</b>
Fast ignition	<b>Ne</b>
Starter less operation	<b>Ne</b>
Suitable for explosion proof luminaires	<b>Ne</b>
Dimmable by conventional dimmers	<b>Ne</b>
Název položky	<b>5 - 079</b>
Třída energetické účinnosti podle 2019/2015	<b>G</b>

### Electrical characteristics

Nominal wattage	<b>21 W</b>
Rated power (W)	<b>20,6 W</b>
Operating voltage (V)	<b>126 V</b>
Type of Voltage	<b>AC</b>
Lamp operating current	<b>0,165 A</b>
Direct connection to the mains	<b>Ne</b>
Lamp power	<b>21 W</b>

Nominal current (A)	0,165 A
Total power (W) (light fitting)	21 W

#### Working conditions

Ambiente temperature for max. luminous flux	25 °C
Burning position	Libovolná
Application	Pro osvětlování potravin
Application	Potraviny
Suitable for emergency lighting	Ne
For application at low temperatures	Ne

#### Physical characteristics

Dimensions (mm)	Ø16 x 849 mm
Packing method	25 - 1
Weight gross	95 g
Weight netto	80 g
Splitter protection	Ne
Tube diameter	16 mm
Lamp shape	Lineární
Length	849 mm
Internal reflector	Ne
Double-walled	Ne

#### EuP Parameters

Average Lifetime B50 (h)	20000 h
Luminescence Life maintenance factor	89,0 %
The rate of premature failures	<1 %
Rated service life	20000 h
Energy consumption (AGGR)	21 kWh/1000h

#### Lighting characteristics

Type of spectrum	Special
Light Colour	FOOD LIGHT
Dominant wavelength	613 nm
Luminous flux	1400 lm
Colour temperature	2920 K
Colour rendering index CRI	70 Ra
Full spectrum lamps	Ne
Colour of light	079
Beam angle Degrees (°)	360 °
Chromaticity coordinates x	0,379
Chromaticity coordinates y	0,290

#### Safety information

Safety instructions	<a href="http://www.nbb.cz">www.nbb.cz</a>
---------------------	--

#### Environmental characteristics

Mercury content	3,00 mg
<b>Energetic characteristics</b>	
Rated efficiency after 100h	99,99 %
Lamp efficacy	66 lm/W
<b>Lamp survival factor (LSF)</b>	
LSF after 2.000 hrs	99,8 %
LSF after 4.000 hrs	99,6 %
LSF after 6.000 hrs	99,3 %
LSF after 8.000 hrs	99,1 %
LSF after 12.000 hrs	98,7 %
LSF after 16.000 hrs	95,0 %
LSF after 20.000 hrs	79,5 %
LSF after 24.000 hrs	50,0 %
<b>Lamp lumen maintenance factor (LLMF)</b>	
LLMF after 2.000 hrs	97,5 %
LLMF after 4.000 hrs	95,4 %
LLMF after 6.000 hrs	94,1 %
LLMF after 8.000 hrs	93,0 %
LLMF after 12.000 hrs	91,5 %
LLMF after 16.000 hrs	90,0 %
LLMF after 20.000 hrs	89,0 %
LLMF after 24.000 hrs	88,2 %
<b>Exclusion of liability</b>	

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

### Warning

If broken in a closed room, we recommend ventilation to reduce the mercury vapor concentration. Use protective equipment while working. Immediately remove the shards so that they do not get injured. After removing the shards, use the technical means for decontamination of mercury. For this purpose we supply decontamination kits, which you can order by phone or in our internet shop. The decontamination kit should not be missed especially in plants where there is a danger of breaking light sources containing mercury, such as stores, warehouses, but can also be used in households. In case of nausea, give first aid and call a physician.

### Notice

Fluorescent tubes of all types require a corresponding type of ballast to operate. A suitable ballast type can be found in the detail of the item (additional products). The quality and type of the ballast greatly affect the life of the fluorescent lamp. NBB Bohemia is not responsible for shortening lamp life when the fluorescent lamp is connected to a ballast type that NBB Bohemia s.r.o. because in such a case we can not guarantee the suitability of using the ballast to the supplied fluorescent tube. When directly connected to the mains voltage without using the ballast, the fluorescent lamp will be destroyed. Fluorescent tubes are not suitable for connection to motion sensors or for connection to frequent switching devices. Frequent switching causes shortening of lamp life. Frequent switching is considered to switch the fluorescent lamp to an interval of less than 20 minutes.

### Popis

Fluorescent tube for meat illumination. Direct replacement of PHILIPS FOOD LIGHT (shade 79).

