


**Product Data Sheet**

Výbojkové svítidlo SYMETRIC

**URANUS 250 MH 240V**  
**2,15A SYMETRIC KVG E40**  
**IP65**



Order number

**912020010**

Unit EAN13 code

**8595209921598**
**General information**

Model/Description	<b>Výbojkové svítidlo</b>
Finish	<b>Průmyslové</b>
Brand/Manufacturer	<b>NBB</b>
Material	<b>Aluminium</b>
Lamp type	<b>výbojka</b>
Degree of protection (IP)	<b>IP65</b>
With light sensor	<b>Ne</b>
Suitable for suspended mounting	<b>Ne</b>
Lamp type	<b>MH výbojka</b>
Nominal voltage (V)	<b>230 - 240 V</b>
Degree of protection (IP)	<b>IP65</b>
Suitable for number of lamps	<b>1</b>
Suitable for wall mounting	<b>Ano</b>
Suitable for traverse mounting	<b>Ano</b>
Suitable for pedestal/floor mounting	<b>Ano</b>
Suitable for light-track mounting	<b>Ne</b>
Suitable for clamp-mounting	<b>Ne</b>
Suitable for ceiling mounting	<b>Ano</b>
Název položky	<b>URANUS 250 MH 240V 2,15A SYMETRIC KVG E40 IP65</b>

**Electrical characteristics**

Nominal wattage	<b>250 W</b>
Rated power (W)	<b>250 W</b>
Capacitor needed to be used	<b>Ano µF</b>
Operating voltage (V)	<b>220 - 240 V</b>

Type of Voltage	AC
Pulse height	5 kV
Lamp operating current	2,15 A
Voltage type	AC
Suitable for lamp power	250 W
Nominal current (A)	1,09 A
System power	275 W

### Working conditions

Operating frequency	50 - 60 Hz
Light source is part of the fixture	Ne
Working temperature of the ballast body -Tc max	100 °C
Burning position	Libovolná
Application	Všeobecné osvětlování
Suitable for through-wiring	Ne
Lamp holder type	E40
With movement sensor	Ne
Type of control gear	Magnetický
Ambient temperature	-30/+50 °C
Fire resistance "D"	Ano
Type of dimming	Nestmívatelné

### Mounting methods/application

Mounting method	Přisazená
-----------------	-----------

### Physical characteristics

Dimensions (mm)	290x220x225 mm
Packing method	1
Weight gross	8200 g
Width	290 mm
Reflector	Ostatní
Colour housing	Šedá
Weight netto	7500 g
Length	225 mm
Height/depth (mm)	220 mm
Material housing	Aluminium
Impact strength	IK10
Type of surface	Matný
Adjustability	Vertikálně

### EuP Parameters

The rate of premature failures	<1 %
Turn-on time	2 s

### Additional information

With lamp	Ne
-----------	----

## Lighting characteristics

Type of light beam	<b>Symetrický</b>
Light sharing	<b>Symetrické</b>
Radiation angle	<b>Široký úhel</b>
Beam angle Degrees (°)	<b>110 °</b>

## Safety information

Insulation class	<b>Třída I</b>
Safety instructions	<b>www.nbb.cz</b>
Protection class	<b>Ochranným vodičem</b>

## Energetic characteristics

Energy Efficiency Index	<b>B2</b>
Lamp Power factor (PF)	<b>0,8</b>

## Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

## Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

## NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

## Popis

**NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí**  
<https://www.nbb.cz/en/> | [hotmail@nbb.cz](mailto:hotmail@nbb.cz)

Copyright CE 2024 NBB Bohemia s.r.o. Všechna práva vyhrazena.