



Product Data Sheet

Výbojkové svítidlo SYMETRIC

URANUS 150 MH/SO
240V ELECTRONIC 0,98A
SYMETRIC RX7s ELT IP65



Order number

912020015

Unit EAN13 code

8595209923950

General information

| | |
|--------------------------------------|--|
| Model/Description | Výbojkové svítidlo |
| Finish | Průmyslové |
| Brand/Manufacturer | NBB |
| Material | Aluminium |
| Degree of protection (IP) | IP65 |
| With light sensor | Ne |
| Suitable for suspended mounting | Ne |
| Lamp type | MH výbojka |
| Nominal voltage (V) | 230 - 240 V |
| Degree of protection (IP) | IP65 |
| Suitable for number of lamps | 1 |
| Suitable for wall mounting | Ano |
| Control gear included | Ano |
| Suitable for traverse mounting | Ano |
| Suitable for pedestal/floor mounting | Ano |
| Suitable for light-track mounting | Ne |
| Suitable for clamp-mounting | Ne |
| Suitable for ceiling mounting | Ano |
| Dimmable by conventional dimmers | Ne |
| Název položky | URANUS 250 HPS 240V 3,00A SYMETRIC KVG E40 IP65 |

Electrical characteristics

| | |
|-----------------------|--------------------|
| Nominal wattage | 250 W |
| Operating voltage (V) | 220 - 240 V |
| Type of Voltage | AC |

| | |
|---------------------------------|---------|
| Pulse height | 5 kV |
| Lamp operating current | 3,00 A |
| Voltage type | AC |
| Suitable for lamp power | 250 W |
| Nominal current (A) | 0,625 A |
| System power | 165 W |
| Total power (W) (light fitting) | 275 W |

Working conditions

| | |
|--------------------------------------|-----------------------|
| Output frequency of ballast (driver) | 40 kHz |
| Operating frequency | 50 - 60 Hz |
| Light source is part of the fixture | Ne |
| Burning position | Libovolná |
| Application | Všeobecné osvětlování |
| Suitable for through-wiring | Ne |
| Lamp holder type | E40 |
| With movement sensor | Ne |
| Type of control gear | Magnetický |
| Ambient temperature | -20/+40 °C |
| Fire resistance "D" | Ano |
| Type of dimming | Nestmívatelné |

Physical characteristics

| | |
|-------------------------|----------------|
| Dimensions (mm) | 290x220x225 mm |
| Packing method | 1 |
| Weight gross | 8200 g |
| Spacing of fixing holes | 80 mm |
| Width | 290 mm |
| Reflector | Ostatní |
| Colour housing | Šedá |
| Weight netto | 7500 g |
| Length | 220 mm |
| Height/depth (mm) | 225 mm |
| Material housing | Aluminium |
| Impact strength | IK10 |
| Type of surface | Matný |
| Adjustability | Vertikálně |

EuP Parameters

| | |
|----------------------------|-------|
| Time to 60 % luminous flux | 180 s |
|----------------------------|-------|

Additional information

| | |
|-----------|----|
| With lamp | Ne |
|-----------|----|

Lighting characteristics

| | |
|-----------------|-------------|
| Light sharing | Symetrické |
| Radiation angle | Široký úhel |

| | |
|------------------------|-------|
| Beam angle Degrees (°) | 110 ° |
|------------------------|-------|

Safety information

| | |
|---------------------|--|
| Insulation class | Ochranným vodičem |
| Safety instructions | www.nbb.cz |
| Protection class | Ochranným vodičem |

Energetic characteristics

| | |
|------------------------|-----|
| Lamp Power factor (PF) | 0,9 |
|------------------------|-----|

Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

Popis

NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí

<https://www.nbb.cz/en/> | hotmail@nbb.cz

Copyright CE 2024 NBB Bohemia s.r.o Všechna práva vyhrazena.