



Product Data Sheet

Výbojkové svítidlo SYMETRIC

URANUS 70 MH/SO 240V
ELECTRONIC 0,98A
SYMETRIC RX7s ELT IP65



Order number

912010006

Unit EAN13 code

8595209943088

General information

Model/Description	Výbojkové svítidlo
Finish	Průmyslové
Brand/Manufacturer	NBB
Material	Aluminium
Lamp type	MH nebo sodíková výbojka
Degree of protection (IP)	IP65
With light sensor	Ne
Suitable for suspended mounting	Ne
Lamp type	MH výbojka
Nominal voltage (V)	230 - 240 V
Degree of protection (IP)	IP65
Suitable for number of lamps	1
Suitable for wall mounting	Ano
Control gear included	Ano
Suitable for traverse mounting	Ano
Suitable for pedestal/floor mounting	Ano
Suitable for light-track mounting	Ne
Suitable for clamp-mounting	Ne
Suitable for ceiling mounting	Ano
Dimmable by conventional dimmers	Ne
Název položky	URANUS 70 MH/SO 240V 0,98A EVG SYMETRIC RX7s IP65

Electrical characteristics

Nominal wattage	70 W
Rated power (W)	70 W

Operating voltage (V)	220 - 240 V
Type of Voltage	AC
Pulse height	5 kV
Lamp operating current	1,8 A
Voltage type	AC
Suitable for lamp power	70 W
Nominal current (A)	0,40 A
System power	77 W
Total power (W) (light fitting)	80,3 W

Working conditions

Operating frequency	50 - 60 Hz
Working temperature of the ballast body -Tc max	45 °C
Hot restart	Ne
Burning position	Libovolná
Installation height (m)	4 - 6 m
Application	Všeobecné osvětlování
Suitable for through-wiring	Ne
Lamp holder type	RX7s
With movement sensor	Ne
Type of control gear	Elektronický nestmívatelný
Ambient temperature	35 °C
Fire resistance "D"	Ano
Type of dimming	Nestmívatelné

Physical characteristics

Numbers of ballasts	1
Dimensions (mm)	282 x 212 x2 15 mm
Packing method	1
Spacing of fixing holes	80 mm
Width	282 mm
Reflector	Ostatní
Colour housing	Šedá
Weight netto	3600 g
Length	215 mm
Height/depth (mm)	212 mm
Material housing	Aluminium
Impact strength	IK10
Type of surface	Matný
Adjustability	Vertikálně

EuP Parameters

Bulb type (size) for which is the luminaire designed.	Čirá
Energy consumption (AGGR)	80,3 kWh/1000h
Turn-on time	180 s

Additional information

Note	Metal Halogenové i sodíkové výbojky
With lamp	Ne

Lighting characteristics

Light sharing	Symetrické
Radiation angle	Široký úhel
Beam angle Degrees (°)	110 °

Safety information

Insulation class	Třída I
Safety instructions	www.nbb.cz
Protection class	Ochranným vodičem

Energetic characteristics

Energy Efficiency Index	B2
Lamp Power factor (PF)	0,9
Ballast efficiency (%)	85 %

Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

Popis

NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí
<https://www.nbb.cz/en/> | hotmail@nbb.cz

Copyright CE 2024 NBB Bohemia s.r.o Všechna práva vyhrazena.