



NBB Bohemia s.r.o.

Výroba a prodej osvětlovací techniky, Sídliště 693, 407 22 Benešov nad Ploučnicí



Product Data Sheet

Kancelářské zářivkové svítidlo

MINA T5 2x54W EVG PAR IP20



Order number

910710065

Unit EAN13 code

8595209944214

General information

| | |
|----------------------------------|-----------------------------------|
| Model/Description | Zářivkové svítidlo |
| Brand/Manufacturer | NBB |
| Material | plech |
| Lamp type | T5 |
| Nominal service life (h) | 50000 h |
| Degree of protection (IP) | IP20 |
| Dimmable | Ne |
| Suitable for suspended mounting | Ano |
| Lamp type | Zářivka T5 (16mm) |
| Nominal voltage (V) | 220 - 240 V |
| Degree of protection (IP) | IP20 |
| Suitable for number of lamps | 2 |
| Dimmable by conventional dimmers | Ne |
| Název položky | MINA T5 2x54W EVG PAR IP20 |

Electrical characteristics

| | |
|--|------------------------------|
| Nominal wattage | 108 W |
| Operating voltage (V) | 220 - 240 V |
| Type of Voltage | AC |
| Lowest permitted operating voltage (V) | 190 V |
| Lamp power | 54 W |
| Circuit | Paralelně-kompenzační |
| Voltage type | AC |
| Lamp power at multiwatt | Ostatní |
| Nominal current (A) | 0,470 A |

Working conditions

| | |
|---|----------------------------|
| Operating frequency | 50 - 60 Hz |
| Light source is part of the fixture | Ne |
| Working temperature of the ballast body -Tc max | 75 °C |
| Hot restart | Ano |
| Protection against overvoltage | Ano |
| Burning position | Horizontální |
| Installation height (m) | 2 - 4 m |
| Application | Všeobecné osvětlování |
| Suitable for through-wiring | Ne |
| Lamp holder type | G5 |
| Type of control gear | Elektronický nestmívatelný |
| Ambient temperature | -10/+40 °C |
| Suitable for light line configuration | Ne |
| Suitable for emergency lighting | Ne |
| Fire resistance "D" | Ano |
| Suspension supplied with the product | Ano |
| Fit for monitor workplace | Ano |
| Type of dimming | Nestmívatelné |
| Emergency unit integrated | Ne |

Physical characteristics

| | |
|---------------------|--------------------|
| Numbers of ballasts | 1 |
| Dimensions (mm) | 1222 x 103 x 81 mm |
| Packing method | 1 |
| Weight gross | 4,8 g |
| Width | 103 mm |
| Reflector | Vysoce leštěný |
| Height | 81 mm |
| Colour housing | Bílá |
| Weight netto | 4600 g |
| Type of grid | Vysoce leštěná |
| Length | 1222 mm |
| Material housing | Ocelový plech |
| Impact strength | IK06 |
| Type of surface | Lesklý |

EuP Parameters

| | |
|------------------------------------|---------|
| Average Lifetime B50 (h) | 50000 h |
| Number of maximal switching cycles | 50000 |
| The rate of premature failures | <1 % |
| Rated service life | 50000 h |
| Turn-on time | <1 s |

Additional information

| | |
|-----------|----|
| With lamp | Ne |
|-----------|----|

Lighting characteristics

| | |
|---|------------|
| Direct-/indirect proportion separately controllable | Ano |
| Light outlet | Přímé |
| Light sharing | Symetrické |
| Colour | Bílá |

Safety information

| | |
|---------------------|--|
| Insulation class | Třída I |
| Safety instructions | www.nbb.cz |
| Protection class | Ochranným vodičem |

Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

Popis

NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí
<https://www.nbb.cz/en/> | hotmail@nbb.cz

Copyright CE 2024 NBB Bohemia s.r.o. Všechna práva vyhrazena.