



Product Data Sheet

Zářivkové svítidlo přisazené

CLAUDIA 258 EVG PAR EM3h IP20

Order number

910390240

Unit EAN13 code

8595209936585


General information

| | |
|----------------------------------|--|
| Model/Description | Zářivkové svítidlo |
| Finish | Kancelářské s leštěnou mřížkou a nouzovým modulem |
| Brand/Manufacturer | NBB |
| Material | Body steel 0,5mm/Louver aluminium 0,3 mm |
| Lamp type | T8 |
| Nominal service life (h) | 50000 h |
| Degree of protection (IP) | IP20 |
| Dimmable | Ne |
| Autonomy | 1 h |
| Suitable for suspended mounting | Ano |
| Lamp type | Zářivka T8 (26mm) |
| Type of luminaire | Mřížkové svítidlo |
| Nominal voltage (V) | 230 - 240 V |
| Suitable for number of lamps | 2 |
| Suitable for wall mounting | Ne |
| Dimmable by conventional dimmers | Ne |
| Název položky | CLAUDIA 258 EVG PAR EM3h IP20 |
| Typ nouzového provozu | Trvalý |

Electrical characteristics

| | |
|-----------------------|--------------------|
| Nominal wattage | 2 x 58 W |
| Rated power (W) | 2 x 58,0 W |
| Operating voltage (V) | 198 - 264 V |
| Endurance | 320 V |
| Type of Voltage | AC |

| | |
|---------------------------------|-----------------------|
| Voltage battery | 6 V |
| Lamp power | 58 W |
| Circuit | Paralelně-kompenzační |
| Voltage type | AC/DC |
| Lamp power at multiwatt | Ostatní |
| Nominal current (A) | 0,50 A |
| Total power (W) (light fitting) | 120 W |

Working conditions

| | |
|---|----------------------------|
| Brand of the light source | NARVA |
| Battery Life | 1000 cyklů |
| Charging time | 24 h |
| Output frequency of ballast (driver) | 40 kHz |
| Operating frequency | 50 - 60 Hz |
| Battery type | NiCD |
| charging control | Ano |
| Battery capacity | 2500 mAh |
| Light source is part of the fixture | Ne |
| Permanent connection to mains supply | Ano |
| Hot restart | Ano |
| Heat protection | Ano |
| Protection against damage during power failure | Ano |
| Protection against overvoltage | Ano |
| Burning position | Horizontální |
| Installation height (m) | 3 - 5 m |
| Installation on flammable surfaces | Ano |
| Application | Všeobecné osvětlování |
| Lamp holder type | G13 |
| Type of control gear | Elektronický nestmívatelný |
| Ambient temperature | -20/+40 °C |
| Suitable for light line configuration | Ne |
| Suitable for emergency lighting | Ano |
| Fire resistance "D" | Ano |
| Fit for monitor workplace | Ano |
| Direct-/indirect proportion separately switchable | Ano |

Mounting methods/application

| | |
|-----------------|-----------|
| Mounting method | Přisazené |
|-----------------|-----------|

Physical characteristics

| | |
|---------------------|--------------------|
| Numbers of ballasts | 1 |
| Type of connector | 3P |
| Dimensions (mm) | 1585 x 360 x 70 mm |
| Packing method | 1 |
| Type of grille | Parabolická |
| Width | 360 mm |
| Reflector | Vysoce leštěný |
| Colour housing | Bílá |

| | |
|---------------------------------|----------------|
| Weight netto | 5350 g |
| Type of grid | Vysoce leštěná |
| With switch | Ne |
| Ball-proof | Ne |
| Length | 1585 mm |
| Height/depth (mm) | 70 mm |
| Material housing | Ocelový plech |
| Material of grid | Aluminium |
| Impact strength | IK06 |
| Power cable with quick coupling | Ano |
| Type of surface | Lesklý |
| Grid perforated | Ne |
| Reflector perforated | Ne |

EuP Parameters

| | |
|------------------------------------|---------------|
| Average Lifetime B50 (h) | 50000 h |
| Time to 60 % luminous flux | 5 s |
| Number of maximal switching cycles | 50000 |
| The rate of premature failures | <1 % |
| Rated service life | 50000 h |
| Energy consumption (AGGR) | 120 kWh/1000h |
| Turn-on time | <2 s |

Additional information

| | |
|-----------|----|
| With lamp | Ne |
|-----------|----|

Lighting characteristics

| | |
|---|------------|
| Anti-glare limiting UGR lengthwise | 20 |
| Anti-glare limiting UGR crosswise | 20 |
| Direct-/indirect proportion separately controllable | Ano |
| Light outlet | Přímé |
| Light sharing | Symetrické |

Safety information

| | |
|---------------------|--|
| Insulation class | Třída I |
| Safety instructions | www.nbb.cz |
| Protection class | Ochranným vodičem |

Energetic characteristics

| | |
|-----------------------------|---------|
| Lamp Power factor (PF) | 0,98 |
| Rated efficiency after 100h | 99,99 % |

Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical

qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

If the luminaire contains batteries

If the luminaire contains rechargeable rechargeable batteries for emergency operation, we provide a 6 months warranty for these batteries from the date of commissioning. This warranty period is valid for both B2C and B2B customers.

Popis

NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí
<https://www.nbb.cz/en/> | hotmail@nbb.cz

Copyright CE 2024 NBB Bohemia s.r.o. Všechna práva vyhrazena.