



**NBB Bohemia s.r.o.**

Výroba a prodej osvětlovací techniky, Sídliště 693, 407 22 Benešov nad Ploučnicí



## Product Data Sheet

Zářivkové svítidlo vestavné

# EMILIA 418 EVG DALI V- OPAL IP40



Order number

**910379450**

Unit EAN13 code

**8595209940469**

### General information

Model/Description	<b>Zářivkové svítidlo</b>
Finish	<b>Vestavné</b>
Brand/Manufacturer	<b>NBB</b>
Material	<b>Body steel 0,5mm/Louver aluminium 0,3 mm</b>
Lamp type	<b>T8</b>
Degree of protection (IP)	<b>IP40</b>
Dimmable	<b>Ano</b>
Built-in depth	<b>100 mm</b>
Lamp type	<b>Zářivka T8 (26mm)</b>
Type of luminaire	<b>Svítidlo s krytem</b>
Electrical connection with connector system	<b>Ne</b>
Nominal voltage (V)	<b>230 - 240 V</b>
Degree of protection (IP)	<b>IP20</b>
Suitable for number of lamps	<b>4</b>
Control gear included	<b>Ne</b>
Dimmable by conventional dimmers	<b>Ne</b>
Název položky	<b>EMILIA 418 EVG DALI V-OPAL IP40</b>
S rozhraním DALI	<b>Ano</b>

### Electrical characteristics

Nominal wattage	<b>4 x 18 W</b>
Rated power (W)	<b>72 W</b>
Operating voltage (V)	<b>198 - 264 V</b>
Type of Voltage	<b>AC</b>
Lowest permitted operating voltage (V)	<b>198 V</b>

Lamp power	18 W
Circuit	Paralelně-kompenzační
Voltage type	AC/DC
Ignitor	Není požadován
Lamp power at multiwatt	Ostatní
Nominal current (A)	0,31 A
Total power (W) (light fitting)	72,0 W

#### Working conditions

Output frequency of ballast (driver)	40 kHz
Operating frequency	50 - 60 Hz
Ambiente temperature for max. luminous flux	25 °C
Hot restart	Ano
Protection against damage during power failure	Ano
Protection against overvoltage	Ano
Burning position	Libovolná
Installation height (m)	2 - 5 m
Application	Všeobecné osvětlování
Suitable for through-wiring	Ne
Lamp holder type	G13
Type of control gear	Stmívatelný DALI
Ambient temperature	-10/+40 °C
Suitable for light line configuration	Ne
Suitable for emergency lighting	Ne
Suitable for wall build in	Ne
Fire resistance "D"	Ano
Fire resistance "F"	Ano
Fit for monitor workplace	Ano

#### Mounting methods/application

Mounting method	Do minerálních podhledů a sádrokartonu
Dimensions of installation hole	600 x 600 mm

#### Physical characteristics

Numbers of ballasts	1
Finish diffuzor	Opálový kryt
Type of connector	3P
Dimensions (mm)	595 x 595 x 80 mm
Packing method	1
Weight gross	4290 g
Back reflector	Ne
Width	595 mm
Reflector	Ostatní
Colour housing	Bílá
Weight netto	3890 g
Built-in width	600 mm
Ball-proof	Ne
Length	595 mm

Height/depth (mm)	80 mm
Material housing	Ocelový plech
Built-in length	600 mm
Colour cover	Bílá
Material cover	Opálový plast
Impact strength	IK06
Power cable with quick coupling	Ne
Type of surface	Lesklý
Diameter lamp	26 mm
Swivelling model	Ne
Grid perforated	Ne
Reflector perforated	Ne

#### EuP Parameters

Average Lifetime B50 (h)	50000 h
Factor of functional reliability (LSF) after nom. life	50 %
Number of maximal switching cycles	50000
The rate of premature failures	<1 %
Rated service life	50000 h

#### Additional information

With lamp	Ne
-----------	----

#### Lighting characteristics

Anti-glare limiting UGR lengthwise	19
Anti-glare limiting UGR crosswise	19
Direct-/indirect proportion separately controllable	Ano
Colour controllable (RGB)	Ne
Colour temperature controllable	Ne
Light outlet	Přímé
Light sharing	Symetrické

#### Safety information

Insulation class	Třída I
Safety instructions	<a href="http://www.nbb.cz">www.nbb.cz</a>
Protection class	Ochranným vodičem

#### Energetic characteristics

Energy Efficiency Index	A2
Lamp Power factor (PF)	0,98

#### Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

#### Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use

products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

**NOTICE:**

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

**Popis**

**NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí**  
<https://www.nbb.cz/en/> | [hotmail@nbb.cz](mailto:hotmail@nbb.cz)

Copyright CE 2024 NBB Bohemia s.r.o. Všechna práva vyhrazena.