


**Product Data Sheet**

svítidlo se senzorem

**BELLA 2x40W PIR senzor  
360° IP20 OPAL**

 Order number  
**909999010**

 Unit EAN13 code  
**8595209921895**

**General information**

Model/Description	<b>Žárovkové svítidlo</b>
Finish	<b>S PIR čidlem</b>
Brand/Manufacturer	<b>NBB</b>
Material	<b>Plast/Opálové sklo/Aluminium</b>
Lamp type	<b>Žárovka</b>
Degree of protection (IP)	<b>IP20</b>
Dimmable	<b>Ne</b>
Lamp type	<b>Žárovka</b>
Type of luminaire	<b>Svítidlo s krytem</b>
Nominal voltage (V)	<b>230 - 240 V</b>
Degree of protection (IP)	<b>IP20</b>
Suitable for number of lamps	<b>2</b>
Suitable for wall mounting	<b>Ano</b>
Dimmable by conventional dimmers	<b>Ne</b>
Název položky	<b>BELLA 2x40W PIR 360° IP20 OPAL</b>

**Electrical characteristics**

Nominal wattage	<b>2 x 40 W</b>
Rated power (W)	<b>2x40,0 W</b>
Operating voltage (V)	<b>230 - 240 V</b>
Type of Voltage	<b>AC</b>
Direct connection to the mains	<b>Ano</b>
Lamp power	<b>40 W</b>
Circuit	<b>Paralelně-kompenzační</b>
Voltage type	<b>AC</b>

Lamp power at multiwatt	Ostatní
-------------------------	---------

### Working conditions

Operating frequency	50 - 60 Hz
Time setting	10 s/3 min
Light control	3 - 2000 lx
Burning position	Libovolná
Suitable for domestic use.	Ano
Installation height (m)	2 - 4 m
Application	Všeobecné osvětlování
Lamp holder type	E27
With movement sensor	Ano
Ambient temperature	-20/+40 °C
Diameter detection range on floor	8 m
Suitable for light line configuration	Ne
Suitable for emergency lighting	Ne
Fire resistance "D"	Ano
Fit for monitor workplace	Ne
Direct-/indirect proportion separately switchable	Ano
Horizontální detekční úhel	360 °

### Mounting methods/application

Mounting method	Přisazené
-----------------	-----------

### Physical characteristics

Dimensions (mm)	Ø300 x 97 mm
Packing method	5 - 1
Weight gross	1900 g
Colour housing	Bílá
Weight netto	1300 g
Diameter	300 mm
Height/depth (mm)	97 mm
Material housing	Plast
Colour cover	Bílá
Material cover	Strukturované sklo
Impact strength	IK03
Type of surface	Matný

### EuP Parameters

The rate of premature failures	<1 %
--------------------------------	------

### Additional information

Note	Pro vnitřní použití
With lamp	Ne

### Lighting characteristics

Anti-glare limiting UGR lengthwise	25
------------------------------------	----

Anti-glare limiting UGR crosswise **25**

Direct-/indirect proportion separately controllable **Ano**

Light outlet **Přímé**

Light sharing **Symetrické**

Beam angle Degrees (°) **360 °**

### Safety information

Insulation class **Třída II**

Safety instructions **www.nbb.cz**

Protection class **Dvojitou izolací**

### Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

### Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

### NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

### Popis

**NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí**  
<https://www.nbb.cz/en/> | [hotmail@nbb.cz](mailto:hotmail@nbb.cz)

Copyright CE 2024 NBB Bohemia s.r.o. Všechna práva vyhrazena.