



NBB Bohemia s.r.o.

Výroba a prodej osvětlovací techniky, Sídliště 693, 407 22 Benešov nad Ploučnicí



Product Data Sheet

Svítlidlo Ø 400 mm SKLO + plech.montura

**KAROLINA 240V Ø 400
mm 2x60W E27 OPÁL
IP44**



Order number

908070000

Unit EAN13 code

8595209911001

General information

Model/Description	Žárovkové svítidlo nástěnné/stropní
Brand/Manufacturer	NBB
Socket	E27
Lamp type	Žárovka
Surface-mounted	Ano
Type of luminaire	Svítlidlo s krytem
Nominal voltage (V)	230 - 240 V
Degree of protection (IP)	IP44
Suitable for number of lamps	2
Suitable for wall mounting	Ano
Suitable for surface mounting	Ano
Suitable for ceiling mounting	Ano
Název položky	KAROLINA 240V Ø 400 mm 2x60W E27 OPÁL IP44

Electrical characteristics

Nominal wattage	2 x 60 W
Lamp power	60 W
Circuit	Ostatní
Voltage type	AC/DC
Lamp power at multiwatt	Ostatní

Working conditions

Burning position	Libovolná
Installation height (m)	2 - 3 m
Lamp holder type	E27

Fire resistance "F"	Ano
Fit for monitor workplace	Ano

Physical characteristics

Spacing of fixing holes	280 mm
Reflector	Ostatní
Colour housing	Bílá
Weight netto	1250 g
Diameter	400 mm
Height/depth (mm)	125 mm
Material housing	Ocelový plech
Colour cover	Bílá
Material cover	Opálové sklo
Type of surface	Matný

Additional information

With lamp	Ne
-----------	----

Lighting characteristics

Anti-glare limiting UGR lengthwise	19
Anti-glare limiting UGR crosswise	19
Light outlet	Přímé
Light sharing	Symetrické

Safety information

Insulation class	Třída I
Safety instructions	www.nbb.cz
Protection class	Ochranným vodičem

Exclusion of liability

Changes to data are subject to prior notice. NBB Bohemia s.r.o. accepts no responsibility for damages caused by inaccurate interpretation of the content on this site.

Notice

This product ranks among electrotechnical products powered by mains voltage 230-240V. For safety reasons, it is recommended that the assembly, connection or disassembly be carried out by a person with an appropriate electrotechnical qualification. Please note that the product may only be put into service with original covers, otherwise there may be a risk of electric shock, especially from the terminal block. Only use the product in places that are suitable for this purpose; do not use products intended for indoor use only in the outdoor environment. When installing or dismantling an emergency luminaire, we recommend disconnecting the power supply otherwise there may be a risk of electric shock. Observe the prescribed position when operating the product and how it is attached. Only connect the product to the rated voltage, or load it only to the maximum permitted power. Install only light sources for this type of luminaire. The manufacturer can not be held responsible for damages resulting from inappropriate connection, connection to an unsuitable distribution system, or damage resulting from the use of an unsuitable light source. Observe the operating values on the label. Do not expose the product to inappropriate weathering or high temperatures unless it is expressly stated that the product is intended to be operated under these conditions. When installing, wiring or disassembling, follow the generally accepted safety precautions.

NOTICE:

The emergency luminaire is energized even after disconnecting the power supply due to its own charged batteries. Therefore, it is recommended that the installation and disassembly be carried out only by a person with the appropriate electrotechnical qualifications.

Do not throw the emergency luminaire into the mixed waste after use. Take it to the nearest store, collection yard, or other designated location for free recycling. You can also deliver the used luminaires for recycling at our sales outlets. Emergency lights and modules contain a rechargeable battery. You can find the list of collection points on the Retel and Ekolamp Collective Systems pages.

Popis

NBB Bohemia s.r.o., Sídliště 693, 407 22 Benešov nad Ploučnicí
<https://www.nbb.cz/en/> | hotmail@nbb.cz

Copyright CE 2024 NBB Bohemia s.r.o Všechna práva vyhrazena.